

POWER AMPLIFIER

3062 (1 kW)

Codan's Power Amplifiers are reliable, affordable, and designed for use with our transceivers. The 3062 power amplifier provides 1 kW PEP output power and is suitable for voice and data operation.

KEY FEATURES

- Continuous mode operation
- High efficiency
- Protection and backup
- Antenna tuner interface
- Front panel indicators
- Amplifier cooling
- Rack mounting

ANTENNA TUNER INTERFACE

The 3062 power amplifier provides an interface to control an external antenna tuner or coupler. The attached transceiver automatically performs a tune when a new transmit frequency is chosen.

Tuning operates on low power, then the high power output engages after the tune is completed.

FRONT PANEL INDICATORS

The front panel indicators provide a comprehensive display of fault conditions including internal fault, VSWR, and over temperature. An LED bar graph is provided to display either the PEP output power or supply current status.

AMPLIFIER COOLING

The 3062 power amplifier has extensive heatsinks with fan forced airflow cooling. For increased reliability and durability, the fans are thermostatically controlled and operate on two speeds depending on the heatsink temperature.

RACK MOUNTING

The 3062 power amplifier and associated power supply unit are designed for use in 19" rack mount configurations and are 5RU high. Front air exhausts allows the 3062 amplifier to be easily installed in virtually any type of 19" rack.



TRANSCIVER INTERFACE

Codan's Sentry-H 6120-BM and Envoy transceivers provide users with a simple interface to control and operate the 3062 power amplifier. Fault conditions are automatically detected and reported to the user via the transceiver interface. The 3062 power amplifier automatically switches to stand-by mode when it is not being used, or when the attached transceiver is powered off.

CONTINUOUS MODE OPERATION

The 3062 power amplifier is rated for 100% continuous operation in all modes for either voice or data applications.

HIGH EFFICIENCY

Advanced switched mode power supplies are used to maximise efficiency of the 3062 power amplifier and to reduce heat. This is achieved by varying the supply voltage on the RF transistors depending upon the current load and modulation.

PROTECTION AND BACKUP

Codan's 3062 power amplifier is fully protected against all load conditions and excessive heat sink temperatures. It is capable of operating with loads of VSWR of up to 3:1 with reduced output power. When excessive VSWR or over temperature occurs, the amplifier switches to by-pass mode to prevent permanent damage. In by-pass mode, the full output power of the attached transceiver is available as a backup to keep the station operational and on-air.

POWER AMPLIFIER

3062 (1 kW)

SPECIFICATIONS	
Compatible transceivers	Envoy X1 Envoy X2 Sentry-H 6120-BM
RF power output	1 kW PEP +/- 1 dB, 600 W average
Frequency range	1.6 to 30 MHz
Input / output impedance	50 Ω
Operating temperature	-10°C to +60°C
Duty cycle	100% normal speech over full temperature range 100% all modes up to maximum ambient 45°C
Power supply	100 to 240 V AC +/-10%, 50 / 60 Hz single phase
Power consumption	1.6 kVA (two-tone), 1.8 kVA maximum
Protection	Safe under all load conditions Bypass to 125 W PEP from transceiver in the event of excess VSWR, excess heatsink temperature or internal fault conditions
Spurious & harmonic emissions	Better than 60 dB below PEP
Intermodulation distortion	Better than 32 dB below PEP
Cooling	Fan forced front panel exhaust Thermostatically controlled dual speed
Size	Amplifier (5RU 19" rack): 22.2 H x 48.3 W x 41.0 D cm Power supply (5RU 19" rack): 22.2 H x 48.3 W x 41.0 D cm
Weight	Amplifier 23.6 kg Power supply 10 kg
Certifications and type approvals	Australian C-tick AS/NZS 4770: 2000 Electrical safety AS/NZS 60950 - EN 60950 CE compliance

Values noted are typical. Equipment descriptions and specifications subject to change without notice or obligation.

DATASHEET: 3062 1kW Power Amplifier, 12-20363-EN, Issue 2 © 2025